

IEC | **Model BMM132MB6F**
 MFG PN: TAX132M2-6-F

PERFORMANCE LOAD VALUES, HIGH VOLTAGE, 60Hz

TYPICAL PERFORMANCE - NOT GUARANTEED VALUES

| TORQUE VALUES | TORQUE (lb-ft) | TORQUE (% FULL LOAD) | PERFORMANCE VALUES | |
|---------------------|----------------|----------------------|----------------------|-----|
| Locked Rotor Torque | - | - | Start Configuration | DOL |
| Pull-Up Torque | - | - | Starting Current (A) | - |
| Breakdown Torque | - | - | No-Load Current (A) | - |
| Full Load Torque | - | - | No-Load Power Factor | - |

| % OF RATED LOAD | 25 | 50 | 75 | 100 | 125 | S.F. 1.25 |
|---------------------|----|----|----|-----|-----|-----------|
| Line Amperes (A) | - | - | - | - | - | - |
| Efficiency (%) | - | - | - | - | - | - |
| Speed (r/min) | - | - | - | - | - | - |
| Power Factor (cosΦ) | - | - | - | - | - | - |
| Input Power (kW) | - | - | - | - | - | - |

Questions? Call 1.888.286.1820